ANKER SOLIX

# Anker SOLIX C2000 Gen 2 Portable Power Station

Efficient Power, Backup Longer

2,048Wh | 2,400W




Phone: +49 (0) 69 9579 7960
Email: support@anker.com

Note: Product specifications and details are subject to change without notice.
Refer to the Anker SOLIX official website for current and accurate information.

LinkedIn

Website

## Anker SOLIX C2000 Gen 2 Portable Power Station

| Capacity | |
|---|---|
| C2000 Capacity | 2,048Wh |
| Extra Battery Capacity | 2,048Wh |
| Maximum Battery Expansion | 1× |
| Maximum Capacity | 4,096Wh (with BP2000 Expansion Battery)<br>5,120Wh (with BP3000 Expansion Battery) |
| **Output** | |
| AC Rated Power | 2,400W |
| Surge Power | 3,000W |
| Peak Power | 4,000W |
| AC Sockets | 4× AC Outlets |
| USB-C Output | 2× 140W, 1× 15W |
| USB-A Output | 1× 12W |
| Car Charger Output | 1× 120W |
| **Input** | |
| AC Input Power | 2,300W |
| DC Input Ports (XT-60) | 800W |
| **Other Specifications** | |
| UPS | 10 ms |
| Life Cycle | 4,000+ (to 80%) |
| Weight | 18.9 kg |
| Dimensions | 459 × 250 × 257 mm |