
Akuvox Smart Intercom




# S532 Information Module Quick Guide

## Unpacking

Before using the device, check the device model and ensure that the shipped box includes the following items:


| | | |
|---|---|---|
|  1 X<br>S532 information Module |  3 X<br>Waterproof label paper |  2 X<br>M3X9.5 Torx head screw |
|  2 X<br>Flush-Mounting rubber plug |  2 X<br>Wall-Mounting rubber plug |  2 X<br>Plastic wall anchor |
|  1 X<br>T10 wrench |  2 X<br>ST4X20 crosshead screw |  1 X<br>Pry bar |

Wall-mounting Accessories (Please find in On-Wall Installation Kit box):


| | | |
|---|---|---|
|  1 X<br>Wall-Mounting box |  1 X<br>Wall-Mounting template |  6 X<br>ST4X20 crosshead screw |
|  6 X<br>Plastic wall anchor |  2 X<br>M4X30 crosshead screw | |

## Installation


### Wall-Mounting Installation





According to the position of the cables on the wall, stick the **wall-mounting template** vertically.




Use a 6mm electric drill to make six screw holes in the locations indicated on the wall-mounting template, each with a depth of 25mm.





Insert six **plastic wall anchors** into the holes.




a. Use six **ST4X20 crosshead screw** to secure the wall-mounting box directly to the wall.


b. Or, if you have an embedded box, fasten four **ST4X20 crosshead screws** to the wall and attach two **M4X30 crosshead screws** to the embedded box to secure the wall-mounting box.





a. Take out the **S532 information Module** and use **pry bar** to remove the front cover.

b. Hold the main unit at a slight tilt (with the bottom slightly outward) and gently slide the upper hooks of the unit into the top hooks of the wall-mounting box.

c. Move the bottom of the main unit backward until it fully aligns with the wall-mounting box.





Fix to **M3X9.5 Torx head screws** into the holes.





a. Use **two wall-mounting rubber plugs** to seal the bottom two holes.


b. Use **flush-mounting rubber plugs** to seal the top two holes.




Place the pre-prepared **label paper** flat on the inner side of the front cover.





Replace the front cover to the **S532 information Module** to complete the installation.





The installation is done.


## Flush-Mounting Installation





Take out the **S532 information Module** and use **pry bar** to remove the front cover.





Place the **S532 information Module** at the installation location and mark the fixing hole positions with a marker.





Remove the box and use a 6mm electric drill the two holes with depth of 25mm.




Insert two **plastic wall nachors** into holes.





Use two **ST4X20 crosshead screws** to attach the **S532 information Module**.





a. Use **two wall-mounting rubber plugs** to seal the bottom two holes.


b. Use **flush-mounting rubber plugs** to seal the top two holes.




Place the pre-prepared **label paper** flat on the inner side of the front cover.




Replace the front cover to the **S532 information Module** to complete the installation.




The installation is done.

# Warranty

1. Akuvox warranty does not cover intentional mechanl damage or destruction caused by improper installation.
2. Do not attempt to modify, alternate, maintain, or repair device by yourself. Akuvox warranty does not apply to damages caused by anvone who is not representative of Akuvox or an Akuvox authorize service provider. Please contact Akuvox Technical Team if the device need to be repaired.

# Get Help

For help or more assistance, contact us at:

https://ticket.akuvox.com/

support@akuvox.com

Scan the QR code to get more videos, guides, and additional product information.

## Notice Information

Information contained in this document is believed to be accurate and reliable at the time of printing. This document is subject to change without notice, any update to this document can be viewed on Akuvox' s website: http://www.akuvox.com © Copyright 2025 Akuvox Ltd. All right reserved.